


# TFT-replacement LJ640U327

Heidenhain BF370 / Contour 12



## Overview:

- 9" TFT replacement Display in Heidenhain BF370 / Contour 12
- replacement for Sharp LJ640U327
- connector and signal timing compatible to the control
- adjustments via On-Screen-Menue
- long-term availability
- front adapter black with holes

## Description:

9" Displays are used as replacement for 9" Sharp LJ640U327 in Heidenhain machines and controls BF370 and Contour 12.

The default timing is compatible to the control, this means after connecting the display the visualisation works correctly. Further adjustments can be made via on-screen-menu. The connector and interface for the graphic-signal and power supply are compatible to the control, so the replacement is easy.

## Technical Data:

### **Overview:**

9" TFT replacment für 9" Sharp LJ640U327

### **Control:**

Heidenhain BF370 / Contour 12

### **Original monitor:**

9" Sharp LJ640U327

### **Interface:**

16pin post plug for ribbon cable

### **Synchronisation/ Timings:**

compatible to control

### **Resolution:**

max. 800x480

### **Adjustments:**

On-Screen-Menu

### **Brightness/ Contrast:**

min. 400cd/qm; 500:1

### **Power supply:**

12 VDC

### **MTBF:**

Backlights min. 5000h

### **Mechanical dimensions:**

depth: 45mm

front adapter: compatible

### **Material:**

front adapter: plastic black

### **Environmental conditons:**

operating temperature 0-50°C

storage temperature 0-65°C

humidity: 10 - 80 % rel. humidity,

not condensing

### **Norms:**

EMV: EN55022 EN55024

EN61010-1

## Part Number:

**10030510**

replacement display Heidenhain  
BF370 / Contour 12